


XMODS™ Custom RC Racing Crystals Set 60-8507

Use this set to change frequencies and race multiple cars. To race with your friends, make sure to use a different crystal set. With the right crystals installed, you can race up to 12 cars at one time.


This set includes 12 crystals, six for the chassis and six for the controller. Each crystal is labeled with a band number (7-12) and a color. Select matching colored and numbered crystals for the chassis and controller. Mismatched crystals do not work. The following table shows the relationship between the band number, frequency, and color:

| Band Bumber | Frequency | Color |
|-------------|-----------|-------------------|
| 7 | 26.975 | gray and brown |
| 8 | 27.025 | brown and red |
| 9 | 27.075 | red and orange |
| 10 | 27.125 | orange and yellow |
| 11 | 27.175 | yellow and green |
| 12 | 27.225 | green and blue |






"rx" indicates chassis crystal



Chassis Crystal



Controller Crystal

1. Turn off the controller and the vehicle.
2. Detach the car body from the chassis by rotating the lock lever clockwise.
3. Remove the **controller crystal** by pulling it straight out. Replace it with a new **controller crystal**.
4. Remove the **chassis crystal** by pulling it straight up. Replace it with a new **chassis crystal**.
5. Reattach the car body to the chassis.

©2003 RadioShack Corporation
All Rights Reserved.
RadioShack and RadioShack.com are trademarks
used by RadioShack Corporation.

